

AL6000S

LAN Socket Modem for Ethernet connectivity. Simple UART to Ethernet bridge and an embedded Web server for Ethernet remote control or M2M applications. Pin compatible with Analog, ISDN and GSM Socket Modems.

Benefits:

- Enables any device to send and receive data via 10/100BaseT Ethernet networks.
- Complete, ready-to-integrate serial-to-Ethernet bridge, ideally suited for a wide range of M2M applications.
- The AL6000S is a lead-free product, conforming to the RoHS standard.
- Flexible IP protocol stack allows integration of user applications.

Functions:

- Serial interface supports DTE speeds to 230.4 Kbps.
- Data transmission modes are transparent or Telnet.
- Command line interface for management and configuration over serial interface or Telnet.
- HTTP server with web page allows monitoring and configuration with WEB browser.
- Ethernet IEEE 802.3u interface with auto-negotiation of 10/100baseT, half/full-duplex and auto-crossover.
- Complete protocol stack: TCP/IP, ARP, ICMP and DHCP.
- Configurable Telnet client and Telnet server with Auto-Dial.
- Central site setup and monitoring of the remote modules.

Functions cont'd:

- Device identification, password protection and security administration.
- Network statistics.
- Transmit block size up to 4Kb supported.
- Flash memory to update the firmware with the latest code or custom features.
- Configurable I/O ports and ADC for monitoring and control.
- Trusted IP-address for Telnet dial-in.
- Optional SPI, CAN or USB interfaces.

Specifications:

- Compact Size: 64.5x26.5x16.2 mm
- Typical Power use: ~100mA.
- Single 5V or 3.3V Supply.
- Serial ITU-T V.24 TTL Interface.
- Conforms to EN60950, EN55022, EN55024 and EN61000
- 2 Year warranty.

Ordering:



AL6000S-5V
AL6000S-3V

Pin Diagram		Pin No	Name	Pin No	Name
<p>Pin diagram showing connections for pins 6 through 32. Labels include TX+, RX+, RX-, TX-, CTS0, TXD0, RTS0, TST1, RESET, TST2, GND, NC, IO0 / LINK-LED, IO1, IO2 / COL-LED, IO3, and various control pins like DTR, DCD, CTS, DSR, RI, TXD, RXD, RTS.</p>	64	NO PIN	64	SPEAKER	
	63	ETH TX+	63	GND Analog	
	62	ETH RX+	62	MICRO IN	
	61	ETH RX-	61	VCC	
	60	ETH TX-	60	NO PIN	
	43 - 59	NO PIN	43 - 59	NO PIN	
	42	CTS0	42	NO PIN	
	41	TXD0	41	GND	
	40	TXD0	40	DTR	
	39	RTS0	39	DCD	
	38	TST1 (don't use)	38	CTS	
	37	RESET	37	DSR	
	36	TST2 (don't use)	36	RI	
	35	GND	35	TXD	
	34	NC	34	RXD	
	33	NC	33	RTS	
	32	IO0 / LINK-LED	32	IO3	
	31	IO1	31	IO2 / COL-LED	
	30	IO2 / COL-LED	30		
	29	IO3	29		
	41	GND	41		
	40	DTR	40		
	39	DCD	39		
	38	CTS	38		
	37	DSR	37		
	36	RI	36		
	35	TXD	35		
	34	RXD	34		
	33	RTS	33		

Operating Conditions	Symbol	Limits	Units
Supply Voltage 5V Version (-5V Version)	VDD	+ 4.75 to + 5.25	VDC
Supply Voltage 3V Version (-3V Version)	VDD	+ 3.15 to + 3.45	VDC
Operating Ambient Temperature	TA	0 to + 70	°C
Extended temperature (ET Version)			

Power Requirements	Typical Current (mA)	Max. Current (mA)
Idle mode, normal data connection	152	175
Sleep Mode	-	-

Product Documentation	Doc Nr.
Designers Guide	AL6000S-E00-102
AT Command Manual	AL6000S-A00-104
Additional Documentation	www.xmodus.ch

Contact Information	
 <p>xmodus swiss GmbH Dachslernstrasse 63 CH-8048 Zürich, Switzerland Phone +41 (0) 44 438 88 82 Web: www.xmodus.ch</p>	
© 2009 xmodus swiss. The information in this document is believed to be accurate in all respects at the time of publication but is subject to change without notice. Xmodus swiss assumes no responsibility for any errors and omissions.	